
- UP TO 100 BAR PRESSURE / TEMPERATURE DISPLAY WITH SCALING / LINEARISATION
- > BATTERY POWERED
- ALARM RELAY, MAX / MIN INFORMATION
- USER SET DISPLAY MESSAGING
- > 5000 POINT DATA LOGGER WITH USB AND NFC INTERFACE



The DM650PM battery powered indicator accepts gauge pressure inputs up to 100 bar and displays the sensor pressure in BAR, PSI or the user's engineering unit on a 6-digit LCD display. The instrument offers an advanced display mode allowing the user to also display one or two (1 to 32) character messages. Additional to the messages, the user may select an alert event to occur when the pressure is within a band. A change-over relay can be used together with the messaging and alerts to provide switching at user-set points. In addition to this, on board datalogging is also available to record process details at up to 5000 points. Force calculations (Ram force for example) can also be performed and displayed.





>

FEATURE HIGHLIGHTS

RELAY

The instrument is equipped with single volt-free change-over type relay. The user may select one of several actions, including deviation operation, with fully adjustable set point and dead-band. An option is provided to trigger an alert event when a relay contact is on.

DATA LOGGING FUNCTION

DM650PM also provides a powerful data logging function. The log points can be set up to 5000 points, each point is time and date stamped together with process value, and relay state information.

The log rate is selectable in steps. The start of log can be delayed if required. Either fixed or rolling logs may be performed.

Two methods of reading the log are available. The USB configuration reads the log and allows the user to save to a text file for export to other programs. The NFC android interface allows data transfer to android phones or tablets, and using the downloadable App, the data can be graphed and forwarded by email, Bluetooth etc. The NFC interface is also capable of starting a new log with different log period and modes.

CALIBRATION / USER LINEARIZATION

5-point calibration can be applied using the USBSpeedLink software.

As well as straight line interpolation, up to 22 points (x,y) of user linearization are available for creating custom curves and corrections.

REAL TIME CLOCK

Date and time can also be displayed with the input pressure. The real-time clock is used to record the data logged points.



INPUT PRESSURE		SPECIFICATIONS @20°C
Туре	Range	Accuracy/stability
Sealed gauge *1	(0 to 3) bar	±0.5% of full scale between (0 to 50) °C *2
	(0 to 30) bar	±0.7% of full scale between (-10 to 80) °C *2
	(0 to 100) bar	
	Other ranges	Contact sales@status.co.uk
Overpressure	4 x pressure range	Up to maximum 350 Bar
Thermal drift	(-10 to 80) °C compensated	
*1 Shows zero bar at 1.0 bar at	osolute	•
*2 Total error band: Maximum	deviation within specified pressu	re and operating temperature range

INPUT		SPECIFICATIONS @20°C
Temperature		
Туре	Range	Accuracy/stability
	(-40 to 110)°C	Typically, ±2.0°C
		·

To maintain full accuracy annual calibration is required contact support@status.co.uk for details

DISPLAY	
Type / options / function	Description
Display height	7.9 mm non-backlit
Display information options	6 digits 14 segment input value plus "Warning"," Transmit", "NFC", "USB",
Some information is displayed	"Log", icons, 8 segment log volume indicators. Maximum, minimum. Date
scrolling.	and time. Custom messages for visual alarms/information. Relay condition.
High intensity LED	Alarm and warning options

RELAY	
Type/ options/ function	Description
Independent relay	Single pole change-over (common, N/o, N/c)
Rating	48 VDC maximum @ 1 A (5 mA minimum)
	28 VAC RMS maximum @ 1 A

USB CONFIGURATION USER IN	TERFACE	
Type / options / function	Description	Notes
Configuration hardware	USB Mini B port	Cable not included
Configuration software	USBSpeedLink	Download www.status.co.uk
Operating system	Microsoft Windows	Win 7 or later
Sensor configuration	User calibration	Up to 5 points
-	Off-set in Bar	Applied by button action
Display configuration	Display mode	Basic with advanced options °C or °F
	Pressure units	Bar, PS I, mBar, Pa, KPa, MPa Kgf/m ² , Kgf/cm ² , Kgf/mm ² Atm, custom units (any)
	Custom units	With 22-point linearization
Pre-set sensor to setpoint	Locks input value to setpoint	For diagnostics
LED alert (advanced mode)	Eight user adjustable pressure bands	Alert LED flash
Warning symbol	Out of range Low battery level	Warning symbol will flash on LCD display



Basic display mode	Update rate	1 s, 5 s
basic display mode		
	Display variable options	Input, input + units, input + units +
	_	temperature
	Temperature units	°C or °F
	Alert LED	
Advanced display mode *1	Display variable (see basic mode) w	rith messaging options
Battery monitor	Alert LED plus message	Relay option link in software
Logger	Set device passkey number	Device passkey is used to protect the
	Clear, start new log	NFC interface.
Other device options	Synchronise clock	
	Write tag, contact address	
	Read, reset maximum and	
	minimum input values	
	Latitude longitude settings	
Relay control	Name(s)	10 characters
	Action	High, low, band, low battery, on, off
	Setpoint	In engineering units
	Dead band	In engineering units
	Latch	On, off
Live data	Read sensor pressure	bar
	Read displayed value	Selected engineering unit
	Read sensor temperature	°C
	Relay 1 state. Relay 2 state	
	Time and date	
*1 Only use advanced display	above -5°C ambient temperature, belo	w use basic display

USB LOGGER USER INTERFACE		
Type / options / function	Description	Notes
Logger hardware	USB Mini B port	Cable not included
Logger software	USBLogLink	Download www.status.co.uk
Operating system	Microsoft Windows	Win 7 or later
Logger	Start/set log parameters	Interval, rate, (delay) start,
	Read log parameters	number of points, rolling or fixed log
	Stop, start new log	
	Synchronise device clock	
	Reset maximum and minimum	
	Synchronise, read clock	
	View log data, graph log data	Save data to CSV file

NFC LOGGER USER INTERFAC ANDROID	E	
Type / options / function	Description	Notes
Logger software	NFCLogLink	@ Google Play Store
Operating system	Android V4.4 Kitkat or later	NFC enabled
Logger	Start, set log parameters	Interval, rate, (delay) start,
	Read log parameters	number of points, rolling or fixed log
	Stop, start new log	
	Synchronise, read clock	
	Reset maximum and minimum	
	View log data, graph log data	Save data to text file
	Transfer data via email etc.	Standard Android functions



GENERAL	
Function	Description
Update rate	1 or 5 seconds
Relay response time	< 10 seconds
Battery	1 x (AA 3.6 V lithium)
Battery life	1 year minimum @20°C (longer depending on options selected)
Clock accuracy	±2 seconds per month typically


ENVIRONMENTAL	
Function	Description
Ambient housing temperature	Operating/storage (-30 to 70)°C
Ambient sensor temperature	Operating (-40 to 110)°C
Ambient humidity	Operating/storage (10 to 90) %RH non-condensing
Protection	IP67, cable entry must be sealed to IP67
USB configuration ambient	(10 to 30)°C

CONNECTIONS	
Sensor to process	1/4 inch BSP male with adaptor options (see accessories)
Output relay	Two-part screw connectors
USB connection	USB mini B port

MECHANICAL	
Enclosure (case)	ABS, grey base, grey clamp ring, side or base mount options
Display cover	Polycarbonate, clear
Case entry	1 x M20 female thread, blanking plug supplied
Front bezel diameter	65 mm
Weight (approximate)	250 g
Material in contact with media	Stainless steel 316L
O-ring	Viton

APPROVALS	
EMC	BS EN 61326
Ingress protection	BS EN 60529
RoHS	Directive 2011/65/EU

DM650PM ORDER CODE							
Case	Style	Input range	Base entry	Side entry 1	Side entry 2	Options	
Side mounted sensor can be wall mounted	/B	/option	/00	/16	/option	Entry options 20 = M20	
Base mounted sensor	/C	/option	/16	/option	/00	NPT = ½ inch NPT	
Input range options in C = (0 to 3), D = (0 to 30) G = (0 to 100)							
Example (0 to 30) bar side mounted sensor M20 entry							
DM650PM	/B	/D /	00 /	16 /20			



ACCESSORIES					
Swivel adaptor ¼ BSPP	SA14BSP				
Swivel adaptor ½ BSPP	SA12BSP				
Swivel adaptor 1/4 NPT	SA14NPT				
Swivel adaptor ½ NPT	SA12NPT				
Swivel adaptor other options available	sales@statinst.com				
Hygienic fittings available	sales@statinst.com				
Configuration software	USBSpeedLink free of charge from www.statinst.com				
USB logging software	USBLogLink free of charge from www.statinst.com				
NFC logging software	NFCLogLink free of charge refer to Google Play Store				
USB lead	USB lead part number 42-200-0001-01				
Battery 3.6 V lithium	Contact sales@statinst.com				

To maintain full accuracy annual calibration is required contact sales@statinst.com for details The data in this document is subject to change. Status Instruments assumes no responsibility for errors

Status Instruments Inc 12H Worlds Fair Drive Somerset, NJ 08873 Tel: (800) 700-3272 Fax: (800) 700-5468 Email: sales@statinst.com Website: www.statinst.com

